

```
#!VERSION=2.3
#!
#! --- WARNING -- WARNING -- WARNING -- WARNING -- WARNING -- WARNING ----
#! This file was created by the Internetworking Configuration Console.
#! It is intended to be modified ONLY by the configurator (INETCFG.NLM).
#! Tampering with this file may cause severe malfunctioning of the system.
#! The configurator will check for tampering and abort if it is detected.
#! -----
#!
#!SERVERTYPE=NORMAL
#!
#!UIMODE=NORMAL
#!
#!BEGINGENLOAD
LOAD SNMP
LOAD BCALLSRV
#!END
#!
#!BEGINTSMLOAD
#!END
#!
#!BEGINBOARD DRVR=CE1000 NAME=CE1000_1 STATUS=ENABLED NUMPORTS=1 DRVRTYPE=LAN
VARIABLEPORTS=NO PORTPARAM=CHANNEL SLOT=2
#Transferred from AUTOEXEC.NCF
#!BEGINPORT NAME=CE1000_1 NUMBER=1 STATUS=ENABLED FRAMES=YES NUMLINKS=1
MEDIA=EtherTsm WANFRAME=UNCONFIGURED
#Transferred from AUTOEXEC.NCF
#!REFCOUNT=1
LOAD CE1000 NAME=CE1000_1_EII FRAME=ETHERNET_II SLOT=2
#!REFCOUNT=1
LOAD CE1000 NAME=CE1000_1_E82 FRAME=Ethernet_802.2 SLOT=2
#!END
#!END
#!
#!BEGINBOARD DRVR=CE100B NAME=CE100B_1 STATUS=ENABLED NUMPORTS=1 DRVRTYPE=LAN
VARIABLEPORTS=NO PORTPARAM=CHANNEL SLOT=3
#Transferred from AUTOEXEC.NCF
#!BEGINPORT NAME=CE100B_1 NUMBER=1 STATUS=ENABLED FRAMES=YES NUMLINKS=1
MEDIA=EtherTsm WANFRAME=UNCONFIGURED
#Transferred from AUTOEXEC.NCF
#!REFCOUNT=1
LOAD CE100B NAME=CE100B_1_EII FRAME=ETHERNET_II SLOT=3
#!END
#!END
#!
#!BEGINPROTO PROTO=TCPIP STATUS=ENABLED
LOAD TcpiP RIP=No Static=Yes LoadSharing=No Forward=Yes VIPASupport=No
#
#!BEGINBIND STATUS=ENABLED
BIND IP CE1000_1_EII MASK=255.0.0.0 ADDRESS=10.0.0.125
#10.0.0.125
#!END
#!BEGINBIND STATUS=ENABLED
BIND IP CE100B_1_EII ARP=Yes Mask=255.255.255.252 Address=192.168.1.2
#192.168.1.2
#!END
#!END
```

```
#!
#!BEGINPROTO PROTO=IPX STATUS=ENABLED
SET Reply To Get Nearest Server=ON
#
LOAD IPXRTR ROUTING=NLSP CFGDIR=SYS:ETC SEQ=1
#
LOAD IPXRTRNM SEQ=1
#
LOAD SPXCONFIG Q=1 A=540 V=54 W=108 R=10 S=1000 I=1200
#
SET IPX NetBIOS Replication Option=1
#
SET Load Balance Local LAN=OFF
#
#!BEGINBIND STATUS=ENABLED
BIND IPX CE1000_1_E82 net=2 seq=1
#2
#!END
#!END
```